

CONFIGURATION WITH NEW CONFIGURATION SOFTWARE

RFID ACTIVATION + USER LIST

1	Click the [Individual Configuration] button
2	Switch on charging station
3	Wait 15 seconds
4	Press [Scan] button
5	Press [Show currently stored User List] button
6	UID numbers of RFID cards that are already stored in the User List, are shown
7	Hold RFID card in front of the RFID module inside the charging station
8	Press [Scan new RFID card] button
9	UID number of new RFID card is shown
10	Press [Add to User List] button
11	The UID number of the new RFID card is added to the User List
12	Press [Save as new User List] button
13	Select checkbox „Access control via RFID“